

Z-Wave Protocol Implementation Conformance Statement

Double-Switch

General Information

Product Identifier:	0x00/9498
Brand Name:	TechniSat
Product Version:	HW: 6 FW: 2.00
Z-Wave Certification #:	ZC10-20036884

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1A91
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	The lifeline group reports the device's status.
2 / 10	Sends basic set commands according to the current state of switch 1 of the device to associated devices.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Double-Switch

3 / 10 Sends basic set commands according to the current state of switch 2 of the device to associated devices.

Supported Command Classes (20):

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Powerlevel	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2