



## Z-Wave Protocol Implementation Conformance Statement

### Power Switch Series

#### General Information

<b>Product Identifier:</b>	PSS-29ZW
<b>Brand Name:</b>	Climax Technology
<b>Product Version:</b>	HW: 255 FW: 4.01
<b>Z-Wave Certification #:</b>	ZC10-20016845

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
---------------------------	-----------------------------

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

##### Nodes

1 / 5	Grouping 1 for "LifeLine": (max node: 5) Switch Binary CC (COMMAND_CLASS_SWITCH_BINARY) Device Reset Locally CC (COMMAND_CLASS_DEVICE_RESET_LOCALLY) When toggling between On/Off, it will send Binary Switch Report to the nodes of Grouping 1.
-------	--

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Power Switch Series

**Supported Command Classes (14):**

Association Group Info	Association V2
Basic	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2