

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Router / USB Power Adaptor

### General Information

<b>Product Identifier:</b>	RMB-35ZW
<b>Brand Name:</b>	Climax Technology
<b>Product Version:</b>	HW: 255 FW: 4.01
<b>Z-Wave Certification #:</b>	ZC10-20016856

### Product Features

<b>Battery Type</b>	NI-MH 200mAh*3
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x000F
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Repeater / Always On Slave

### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	Group 1 for "LifeLine": (maximum node: one) Battery CC (COMMAND_CLASS_BATTERY) Notification CC,V8 (COMMAND_CLASS_NOTIFICATION) Device Reset Locally CC

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Router / USB Power Adaptor

### Supported Command Classes (14):

Association Group Info  
Battery  
Firmware Update Meta-Data V4  
Multi-Channel Association V3  
Powerlevel  
Supervision  
Version V3

Association V2  
Device Reset Locally  
Manufacturer Specific V2  
Notification V8  
Security S2  
Transport Service V2  
Z-Wave Plus Info V2