

Z-Wave Protocol Implementation Conformance Statement

Dimmer

General Information

Product Identifier:	0x00/9497
Brand Name:	TechniSat
Product Version:	HW: 7 FW: 2.00
Z-Wave Certification #:	ZC10-20036883

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1A92
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	The lifeline group reports the device's status.
2 / 10	Sends basic set commands to associated devices, according to the current state of the device.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Dimmer

Supported Command Classes (18):

Association Group Info
Basic V2
Configuration
Firmware Update Meta-Data V4
Meter V4
Powerlevel
Security S2
Switch Multilevel V4
Version V3

Association V2
Central Scene V3
Device Reset Locally
Manufacturer Specific V2
Notification V8
Security S0
Supervision
Transport Service V2
Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2