

## Z-Wave Protocol Implementation Conformance Statement

### Dimmer

#### General Information

**Product Identifier:** 0x00/9497  
**Brand Name:** TechniSat  
**Product Version:** HW: 7 FW: 2.00  
**Z-Wave Certification #:** ZC10-20036883

#### Product Features

**Firmware Updatable** Updatable by Consumer by RF  
**Neutral Wire Required** Yes

#### Z-Wave Product Information

**Supports Z-Wave Beaming Technology?** Yes  
**Supports Z-Wave Network Security?** Yes  
**Supports Z-Wave AES-128 Security S0?** Yes  
**Supports Security S2?** Yes: S2 Authenticated, S2 Unauthenticated  
**SmartStart Compatible?** Yes

#### Z-Wave Technical Information

**Z-Wave Frequency:** CEPT (Europe)  
**Z-Wave Product ID:** 0x1A92  
**Z-Wave Product Type:** 0x0004  
**Z-Wave Hardware Platform:** ZM5101  
**Z-Wave Development Kit Version:** 6.82.00  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	The lifeline group reports the device's status.
2 / 10	Sends basic set commands to associated devices, according to the current state of the device.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Dimmer

**Supported Command Classes (18):**

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V4	Notification V8
Powerlevel	Security S0
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2
----------