

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Dual Pet PIR

General Information

Product Identifier:	PLBW10000
Brand Name:	ABUS
Product Version:	HW: 1 FW: 1.01:00.01
Z-Wave Certification #:	ZC10-20036890

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0004
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	The Lifeline Association is automatically established between the Z-Wave controller and the device during inclusion and defines what information is exchanged between the Z-Wave controller and the device. Notification report Battery report Device Reset Locally Notification Sensor Multilevel Report
2 / 4	When the motion alarm is triggered, it sends a BASIC SET On / Off command to the nodes of group 2

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Dual Pet PIR

Supported Command Classes (17):

Association Group Info
Battery
Device Reset Locally
Manufacturer Specific V2
Powerlevel
Security S2
Supervision
Version V3
Z-Wave Plus Info V2

Association V2
Configuration
Firmware Update Meta-Data V4
Notification V8
Security S0
Sensor Multilevel V5
Transport Service V2
Wake Up V2

Controlled Command Classes (1):

Basic