

## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Dimmer (Dual Plug Simultaneous Control)

### General Information

<b>Product Identifier:</b>	39446 / ZW3107
<b>Brand Name:</b>	Honeywell Home (Resideo)
<b>Product Version:</b>	HW: 255 FW: 5.21
<b>Z-Wave Certification #:</b>	ZC10-20036897

### Product Features

<b>Switch Type</b>	Push Button Illuminated
<b>Switch Load Capacity Watts</b>	300
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3033
<b>Z-Wave Product Type:</b>	0x5044
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Dimmer (Dual Plug Simultaneous Control)

- 2 / 5 Association Group 2 supports Basic Set and is controlled by single pressing the button
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the button

### Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Multilevel V2	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic