

## Z-Wave Protocol Implementation Conformance Statement

### Door/Window Sensor

#### General Information

<b>Product Identifier:</b>	ZD2106BR-7
<b>Brand Name:</b>	Vision
<b>Product Version:</b>	HW: 3 FW: 32.04
<b>Z-Wave Certification #:</b>	ZC12-20050061

#### Product Features

<b>Battery Type</b>	CR2032
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Manufacturer Representative
<b>Battery Quantity</b>	1

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Don't know
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Brazil
<b>Z-Wave Product ID:</b>	0x01D1
<b>Z-Wave Product Type:</b>	0x2001
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door/Window Sensor

2 / 5

\* Group 2 = On/Off Control

### Supported Command Classes (17):

Association Group Information V3

Battery

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S0

Supervision

Version V3

Z-Wave Plus Info V2

Association V2

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Security S2

Transport Service V2

Wake Up V2