

## Z-Wave Protocol Implementation Conformance Statement

### Door / Window Sensor 7 Pro

#### General Information

<b>Product Identifier:</b>	ZWA012-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-20060075

#### Product Features

<b>Color</b>	White
<b>Battery Quantity</b>	1
<b>Battery Type</b>	ER14250

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x000C
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door / Window Sensor 7 Pro

- 2 / 5 Control devices when a magnet or external dry contacts trips
- 3 / 5 Sends out alarm message when a magnet or external dry sensor trips
- 4 / 5 Sends alarm messages when tamper is tripped
- 5 / 5 Control devices when tilting sensor trips

### Supported Command Classes (19):

Association Group Information V3

Battery

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S2

Supervision

Version V3

Z-Wave Plus Info V2

Association V2

Central Scene V3

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Sensor Binary V2

Transport Service V2

Wake Up V2