

## Z-Wave Protocol Implementation Conformance Statement

# AërQ - Temperature & Humidity Sensor

### General Information

<b>Product Identifier:</b>	ZWA009-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-20080086

### Product Features

<b>Color</b>	White
<b>Battery Type</b>	CCR2477H
<b>Battery Quantity</b>	1

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0009
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## AërQ - Temperature & Humidity Sensor

- 2 / 5 High Temperature Notification - Sends a notification to the associated device
- 3 / 5 Low Temperature Notification - Sends a notification to the associated device, when the low temperature threshold is breached.
- 4 / 5 High Humidity Notification - Sends a notification to the associated device, when the high humidity threshold is breached.
- 5 / 5 Low Humidity Notification - Sends a notification to the associated device, when the low humidity threshold is breached.
- 6 / 5 Air Temperature (A multilevel sensor report is sent to the nodes in this group).

### Supported Command Classes (19):

- |                                  |                              |
|----------------------------------|------------------------------|
| Association Group Information V3 | Association V2               |
| Battery                          | Configuration V4             |
| Device Reset Locally             | Firmware Update Meta-Data V5 |
| Indicator V3                     | Manufacturer Specific V2     |
| Multi-Channel Association V3     | Notification V8              |
| Powerlevel                       | Security S2                  |
| Sensor Binary V2                 | Sensor Multilevel V11        |
| Supervision                      | Transport Service V2         |
| Version V3                       | Wake Up V2                   |
| Z-Wave Plus Info V2              |                              |