

Z-Wave Protocol Implementation Conformance Statement

AërQ - Temperature & Humidity Sensor

General Information

Product Identifier:	ZWA009-C
Brand Name:	Aeotec
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC12-20080086

Product Features

Color	White
Battery Type	CCR2477H
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0009
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.12.2
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

AërQ - Temperature & Humidity Sensor

- 2 / 5 High Temperature Notification - Sends a notification to the associated device
- 3 / 5 Low Temperature Notification - Sends a notification to the associated device, when the low temperature threshold is breached.
- 4 / 5 High Humidity Notification - Sends a notification to the associated device, when the high humidity threshold is breached.
- 5 / 5 Low Humidity Notification - Sends a notification to the associated device, when the low humidity threshold is breached.
- 6 / 5 Air Temperature (A multilevel sensor report is sent to the nodes in this group).

Supported Command Classes (19):

- | | |
|----------------------------------|------------------------------|
| Association Group Information V3 | Association V2 |
| Battery | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V5 |
| Indicator V3 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Notification V8 |
| Powerlevel | Security S2 |
| Sensor Binary V2 | Sensor Multilevel V11 |
| Supervision | Transport Service V2 |
| Version V3 | Wake Up V2 |
| Z-Wave Plus Info V2 | |