



Z-Wave Protocol Implementation Conformance Statement

ZCOMBO-G

General Information

Product Identifier: ZCOMBO
Brand Name: First Alert
Product Version: HW: 2 FW: 11.00:07.00
Z-Wave Certification #: ZC10-20076935

Product Features

Firmware Updatable Not Updatable
Outdoor Use No
Color White
Battery Quantity 2
Battery Type AA

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x0003
Z-Wave Product Type: 0x0001
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.81.06
Z-Wave Library Type: Routing Slave
Z-Wave Device Type / Role Type: Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ZCOMBO-G

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 The alarm supports one association group (Lifeline) with up to 1 node, and sends its alarms to that group. Group ID: 0x01, Group Name: Lifeline. The Z-Wave network controller may be set in this group. It's not recommended to modify this association group. All the critical events mentioned in the list of supported events over Notification Command Class will be triggered from the Lifeline association group.

Supported Command Classes (15):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	