

Z-Wave Protocol Implementation Conformance Statement

In-Wall Tamper Resistant Smart Outlet

General Information

Product Identifier:	55256/ZW1002
Brand Name:	Enbrighten
Product Version:	HW: 255 FW: 5.51
Z-Wave Certification #:	ZC10-20076950

Product Features

Switch Type	Push Button Illuminated
Electric Load Type	(No feature option values set for this feature)
Neutral Wire Required	Yes
Switch Load Capacity Watts	1800W
Switch Load Capacity Current	15A
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3234
Z-Wave Product Type:	0x4952
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Tamper Resistant Smart Outlet

Association Group Information

Group # / Max Description

Nodes

- 1 / 5 Z-Wave Plus Lifeline
- 2 / 5 Supports Basic Set and is controlled with the local load
- 3 / 5 Supports Basic Set and is controlled by pressing the On or Off button

Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2