

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave LED Light Bulb

#### General Information

<b>Product Identifier:</b>	52190/ ZW7105
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 1 FW: 4.10
<b>Z-Wave Certification #:</b>	ZC10-20096974

#### Product Features

<b>Electric Load Type</b>	Dimmable LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3035
<b>Z-Wave Product Type:</b>	0x4C42
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 5	Z-Wave Plus Lifeline

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave LED Light Bulb

### Supported Command Classes (15):

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Security S0	Security S2
Supervision	Switch Multilevel
Transport Service V2	Version V3
Z-Wave Plus Info V2	