

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall 3-Speed Fan Control

### General Information

<b>Product Identifier:</b>	55258/ZW4002
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 255 FW: 5.50
<b>Z-Wave Certification #:</b>	ZC10-20086955

### Product Features

<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Central Scene
<b>Switch Load Capacity Volt-Ampere</b>	2.5
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3337
<b>Z-Wave Product Type:</b>	0x4944
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Fan Switch / Always On Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall 3-Speed Fan Control

- 2 / 5 Supports Basic Set and is controlled with the local load
- 3 / 5 Supports Basic Set and is controlled by double pressing the On or Off button

### Supported Command Classes (16):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2