

Z-Wave Protocol Implementation Conformance Statement

Heatit Z-Smoke Detector 230V

General Information

Product Identifier:	4512689
Brand Name:	Heatit controls
Product Version:	HW: 255 FW: 4.01
Z-Wave Certification #:	ZC10-20076952

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Type	NI-MH 200mAh
Battery Quantity	3

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x3601
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Heatit Z-Smoke Detector 230V

2 / 1

Basic CC (COMMAND_CLASS_BASIC) #.When the Smoke Detector is active, it will send Basic Set (0xFF) in Group 2. #.When the Smoke Detector is restored, it will send Basic Set (0x00) in Group 2.

Supported Command Classes (15):

Association Group Info	Association V2
Battery	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Sensor Multilevel V11	Supervision
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2