

## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Smart Dimmer (Dual Plug with Pass through Outlet)

### General Information

<b>Product Identifier:</b>	55252/ ZW3105
<b>Brand Name:</b>	Jasco
<b>Product Version:</b>	HW: 255 FW: 5.50
<b>Z-Wave Certification #:</b>	ZC10-20086958

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Loads Controlled</b>	2
<b>Switch Load Capacity Current</b>	15
<b>Switch Load Capacity Watts</b>	1800
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3134
<b>Z-Wave Product Type:</b>	0x5044
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Smart Dimmer (Dual Plug with Pass through Outlet)

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 5            Z-Wave Plus Lifeline
- 2 / 5            Association Group 2 supports Basic Set and is controlled with the local load
- 3 / 5            Association Group 3 supports Basic Set and is controlled by double pressing the button

**Supported Command Classes (15):**

- |                      |                          |
|----------------------|--------------------------|
| Application Status   | Association Group Info   |
| Association V2       | Basic V2                 |
| Central Scene V3     | Configuration V4         |
| Device Reset Locally | Manufacturer Specific V2 |
| Powerlevel           | Security S2              |
| Supervision          | Switch Multilevel V4     |
| Transport Service V2 | Version V3               |
| Z-Wave Plus Info V2  |                          |