

Z-Wave Protocol Implementation Conformance Statement

Luxy Smart Light

General Information

Product Identifier:	ZMNHQD1
Brand Name:	QUBINO
Product Version:	HW: 1 FW: 11.00:11.00
Z-Wave Certification #:	ZC10-20096982

Product Features

Color	Gray
Neutral Wire Required	Yes
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0051
Z-Wave Product Type:	0x0008
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Color Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Luxy Smart Light

2 / 5 COMMAND_CLASS_BASIC_V2, BASIC_SET_V2
3 / 5 COMMAND_CLASS_SWITCH_MULTILEVEL_V4, SWITCH_MULTILEVEL_SET_V4
4 / 5 COMMAND_CLASS_SWITCH_COLOR_V3, SWITCH_COLOR_SET_V3

Supported Command Classes (17):

Association Group Information V3	Association V2
Basic V2	Configuration
Device Reset Locally	Manufacturer Specific V2
Notification V8	Powerlevel
Security S0	Security S2
Sound Switch	Supervision
Switch Color V3	Switch Multilevel V4
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (3):

Basic V2	Switch Color V3
Switch Multilevel V4	