



Z-Wave Protocol Implementation Conformance Statement

Smart Module

General Information

Product Identifier:	FGS-214
Brand Name:	FIBARO
Product Version:	HW: 4 FW: 5.00
Z-Wave Certification #:	ZC10-20086957

Product Features

Color	Black
Electric Load Type	Incandescent
Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x0404
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Module

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 1 Reports the device status and allows for assigning single device only (main controller by default).
- 2 / 5 Is used to turn the associated devices on/off reflecting input operation (uses Basic command class).

Supported Command Classes (21):

- Application Status
- Association V2
- Central Scene V3
- CRC16 Encapsulation
- Firmware Update Meta-Data V4
- Multi-Channel Association V3
- Powerlevel
- Security S0
- Supervision
- Transport Service V2
- Z-Wave Plus Info V2
- Association Group Information V2
- Basic
- Configuration
- Device Reset Locally
- Manufacturer Specific V2
- Notification V8
- Protection V2
- Security S2
- Switch Binary
- Version V2

Controlled Command Classes (1):

- Basic