

Z-Wave Protocol Implementation Conformance Statement

Slim Smart Door/Window Sensor

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | 52249/ZW6308 |
| Brand Name: | Jasco |
| Product Version: | HW: 1 FW: 7.07 |
| Z-Wave Certification #: | ZC12-20080113 |

Product Features

| | |
|---------------------------|-----------------------------|
| Battery Type | CR2450 |
| Firmware Updatable | Updatable by Consumer by RF |
| Battery Quantity | 1 |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x3336 |
| Z-Wave Product Type: | 0x4953 |
| Z-Wave Hardware Platform: | ZGM130 |
| Z-Wave Development Kit Version: | 7.13.5 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
| Nodes | |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Slim Smart Door/Window Sensor

Supported Command Classes (18):

| | |
|------------------------------|----------------------------------|
| Application Status | Association Group Information V3 |
| Association V2 | Battery |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta-Data V5 | Indicator V3 |
| Manufacturer Specific V2 | Multi-Channel Association V3 |
| Notification V8 | Powerlevel |
| Security S2 | Supervision |
| Transport Service V2 | Version V3 |
| Wake Up V2 | Z-Wave Plus Info V2 |