



Z-Wave Protocol Implementation Conformance Statement

Portable Remote, Simple Controller, 2 Button

General Information

Product Identifier: 53829/ZW5313
Brand Name: Jasco
Product Version: HW: 1 FW: 7.04
Z-Wave Certification #: ZC12-20090119

Product Features

Firmware Updatable Updatable by Consumer by RF
Battery Type CR2032
Battery Quantity 2
Z-Wave Scene Type Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x3136
Z-Wave Product Type: 0x4843
Z-Wave Hardware Platform: ZGM130
Z-Wave Development Kit Version: 7.13.6
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Central Scene Device / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Portable Remote, Simple Controller, 2 Button

- 2 / 5
- Association Group 2 supports Basic Set and is controlled by pressing the UP or Down button once.
- 3 / 5
- Association Group 3 supports Basic Set and is controlled by double pressing the UP or Down button twice.

Supported Command Classes (19):

Application Status	Association Group Information V3
Association V2	Battery
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	