

Z-Wave Protocol Implementation Conformance Statement

ZOE POWER H

General Information

Product Identifier:	HZ06100
Brand Name:	Master
Product Version:	HW: 2 FW: 5.01:05.02
Z-Wave Certification #:	ZC10-20096969

Product Features

Switch Type	Toggle
Neutral Wire Required	Yes
Switch Load Capacity Watts	920
Switch Load Capacity Current	4
Color	Black
Loads Controlled	2
Electric Load Type	Fluorescent Incandescent Inductive (e.g. Motor) LED

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ZOE POWER H

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0051
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1	Lifeline group (reserved for communication with the main controller), 1 node allowed.
2 / 16	Basic on/off (triggered at change of the output Q1 state and reflecting its state) up to 16 nodes.
3 / 16	Switch binary report (triggered at change of the output Q1 state and reflecting its state) up to 16 nodes.
4 / 16	Power meter report (triggered at change of the output Q1 state) up to 16 nodes
5 / 16	Basic on/off (triggered at change of the output Q2 state and reflecting its state) up to 16 nodes.
6 / 16	Switch binary report (triggered at change of the output Q2 state and reflecting its state) up to 16 nodes.
7 / 16	Power meter report (triggered at change of the output Q2 state) up to 16 nodes.
8 / 16	Multilevel sensor report (triggered at change of temperature sensor) up to 16 nodes.

Supported Command Classes (15):

Association Group Information V2	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Sensor Multilevel V7	Switch All
Switch Binary	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic