

## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Smart Dimmer (Dual Plug with Simultaneous Control)

### General Information

<b>Product Identifier:</b>	55251/ ZW3107
<b>Brand Name:</b>	Enbrighten
<b>Product Version:</b>	HW: 255 FW: 5.50
<b>Z-Wave Certification #:</b>	ZC10-20086965

### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	2.5
<b>Switch Load Capacity Watts</b>	300
<b>Switch Type</b>	Push Button Illuminated
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3133
<b>Z-Wave Product Type:</b>	0x5044
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Smart Dimmer (Dual Plug with Simultaneous Control)

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5            Z-Wave Plus Lifeline

2 / 5            Association Group 2 supports Basic Set and is controlled with the local load

3 / 5            Association Group 3 supports Basic Set and is controlled by double pressing the button

**Supported Command Classes (15):**

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	