

Z-Wave Protocol Implementation Conformance Statement

FGS-224

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | FGS-224 |
| Brand Name: | FIBARO |
| Product Version: | HW: 4 FW: 5.00 |
| Z-Wave Certification #: | ZC10-20096968 |

Product Features

| | |
|---------------------------|-----------------------------|
| Electric Load Type | Incandescent |
| Firmware Updatable | Updatable by Consumer by RF |
| Z-Wave Scene Type | Central Scene |
| Color | Black |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---------------------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x1000 |
| Z-Wave Product Type: | 0x0204 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.82.00 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | On/Off Power Switch / Always On Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FGS-224

- 2 / 5 Is used to turn the associated devices on/off reflecting input operation for 1st channel (uses Basic command class).
- 3 / 5 Is used to turn the associated devices on/off reflecting input operation for 2nd channel (uses Basic command class).

Supported Command Classes (22):

- Application Status
- Association V2
- Central Scene V3
- CRC16 Encapsulation
- Firmware Update Meta-Data V4
- Multi-Channel Association V3
- Notification V8
- Protection V2
- Security S2
- Switch Binary
- Version V2
- Association Group Information V2
- Basic
- Configuration
- Device Reset Locally
- Manufacturer Specific V2
- Multi-Channel V4
- Powerlevel
- Security S0
- Supervision
- Transport Service V2
- Z-Wave Plus Info V2

Controlled Command Classes (1):

- Basic