

Z-Wave Protocol Implementation Conformance Statement

Enbrighten Z-Wave Plus In-Wall Smart Dimmer, No Neutral, LED-CFL

General Information

Product Identifier:	52252/52253/ZW3012
Brand Name:	Enbrighten
Product Version:	HW: 1 FW: 7.06
Z-Wave Certification #:	ZC12-20120145

Product Features

Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	300
Switch Type	Decorator Paddle Push with Indicator
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3333
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.6
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Enbrighten Z-Wave Plus In-Wall Smart Dimmer, No Neutral, LED-CFL, White and Light Almond Paddles

2 / 5 Association Group 2 supports Basic Set and is controlled with the local load

3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the ON/OFF button

Supported Command Classes (18):

Application Status	Association Group Information V3
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2