

## Z-Wave Protocol Implementation Conformance Statement

### DIMMER SWITCH 700

#### General Information

<b>Product Identifier:</b>	ZEN72
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-21030190

#### Product Features

<b>Electric Load Type</b>	Dimmable LED Dimmable MLV (Magnetic) Incandescent LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	150
<b>Z-Wave Scene Type</b>	Central Scene
<b>Color</b>	White
<b>Neutral Wire Required</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## DIMMER SWITCH 700

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xA002
<b>Z-Wave Product Type:</b>	0x7000
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Lifeline Communication to the hub.
2 / 5	Basic set to Group 2.
3 / 5	Switch multilevel to Group 3.

**Supported Command Classes (17):**

Association Group Information V3	Association V3
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	