

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Plus Switch

#### General Information

**Product Identifier:** SQR14102\*\*Z (\*\* means color code)  
**Brand Name:** Square D  
**Product Version:** HW: 1 FW: 1.17  
**Z-Wave Certification #:** ZC12-21030193

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated  
SmartStart Compatible? Yes

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x1106  
**Z-Wave Product Type:** 0x000E  
**Z-Wave Hardware Platform:** ZGM130  
**Z-Wave Development Kit Version:** 7.13.6  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Binary Switch / Always On Slave

#### Association Group Information

**Group # / Max**    **Description**

##### Nodes

1 / 5            Lifeline: Send device reset locally notification StatusReport: On/Off status report PowerReport: Power metering report  
2 / 5            Sends Basic Set to associated devices, when press ON Button and OFF Button at same time.

##### Supported Command Classes (19):

Application Status	Association Group Information V3
Association V2	Basic V2
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Meter V5

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus Switch