

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Plus Plug-in

#### General Information

<b>Product Identifier:</b>	SQR62102WHZ
<b>Brand Name:</b>	Square D
<b>Product Version:</b>	HW: 1 FW: 1.05
<b>Z-Wave Certification #:</b>	ZC12-21050231

#### Product Features

<b>Z-Wave Scene Type</b>	Central Scene
--------------------------	---------------

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x1108
<b>Z-Wave Product Type:</b>	0x000E
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 5	Members of this group will receive unsolicited messages related to the status of the Plug.
2 / 5	Sends Basic Set to associated devices, when Short press the Program Button 2 times.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus Plug-in

### Supported Command Classes (19):

Application Status	Association Group Information V3
Association V2	Basic V2
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Meter V5
Multi-Channel Association V3	Powerlevel
Protection V2	Security S2
Supervision	Switch Binary V2
Transport Service V2	Version V3
Z-Wave Plus Info V2	