

## Z-Wave Protocol Implementation Conformance Statement

# REMOTE SWITCH

### General Information

<b>Product Identifier:</b>	ZEN34
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-21030192

### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	CR2032
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xF001
<b>Z-Wave Product Type:</b>	0x7000
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Central Scene Device / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## REMOTE SWITCH

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1            Lifeline Communication to the hub.

2 / 5            Basic set to Group 2.

3 / 5            Switch multilevel to Group 3.

**Supported Command Classes (17):**

Association Group Information V3

Battery

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Powerlevel

Supervision

Version V3

Z-Wave Plus Info V2

Association V3

Central Scene V3

Device Reset Locally

Indicator V3

Multi-Channel Association V4

Security S2

Transport Service V2

Wake Up V2