

## Z-Wave Protocol Implementation Conformance Statement

### Smart On/Off Switch

#### General Information

<b>Product Identifier:</b>	MS10ZS
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC12-21040212

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Type</b>	Push Button

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xEE01
<b>Z-Wave Product Type:</b>	0xEE00
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
------------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart On/Off Switch

2 / 5            Send BASIC SET Command

3 / 5            Send BASIC SET Command

### Supported Command Classes (17):

Association Group Information V3

Basic V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific

Powerlevel

Supervision

Transport Service V2

Z-Wave Plus Info V2

Association V3

Central Scene V3

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Security S2

Switch Binary V2

Version V3