



## Z-Wave Protocol Implementation Conformance Statement

### Contact Sensor v2 EU

#### General Information

<b>Product Identifier:</b>	Contact Sensor v2 EU
<b>Brand Name:</b>	Ring
<b>Product Version:</b>	HW: 1 FW: 1.10
<b>Z-Wave Certification #:</b>	ZC12-21040216

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0301
<b>Z-Wave Product Type:</b>	0x0201
<b>Z-Wave Hardware Platform:</b>	EFR32Z
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                      This is the Lifeline group and the following are the supported Command Classes- 1. Notification Report a. See notification CC section for notifications that are sent 2. Battery Report 3. Device Reset Locally Notification

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Contact Sensor v2 EU

### Supported Command Classes (17):

Association Group Information V3

Battery

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Supervision

Version V3

Z-Wave Plus Info V2

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S2

Transport Service V2

Wake Up V2