

## Z-Wave Protocol Implementation Conformance Statement

### Range Extender v2 EU

#### General Information

<b>Product Identifier:</b>	Range Extender v2 EU
<b>Brand Name:</b>	Ring
<b>Product Version:</b>	HW: 1 FW: 1.10
<b>Z-Wave Certification #:</b>	ZC12-21040217

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0301
<b>Z-Wave Product Type:</b>	0x0401
<b>Z-Wave Hardware Platform:</b>	EFR32Z
<b>Z-Wave Development Kit Version:</b>	7.12.1
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Repeater / Always On Slave

#### Association Group Information

##### Group # / Max Description

##### Nodes

1 / 5	This is the Lifeline group and the following are the supported command class - 1. Notification Report a. See notification CC section for notifications that are sent 2. Battery Report 3. Device Reset Locally Notification
-------	---

##### Supported Command Classes (16):

Association Group Information V3	Association V2
Battery	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

Range Extender v2 EU