

Z-Wave Protocol Implementation Conformance Statement

Smart In Wall Dimmer

General Information

Product Identifier:	HS-WX300
Brand Name:	HomeSeer
Product Version:	HW: 1 FW: 1.11
Z-Wave Certification #:	ZC12-21070246

Product Features

Z-Wave Scene Type	Scene & Central Scene
Color	White
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	600W Incandescent, 300W Dimmable LED/CFL
Neutral Wire Required	No
Outdoor Use	No
Electric Load Type	Dimmable Fluorescent Dimmable LED Fluorescent Incandescent LED
Switch Load Capacity Volt-Ampere	120VAC

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart In Wall Dimmer

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x4036
Z-Wave Product Type:	0x4447
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.15.2
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch / Always On Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 5	Group 1 is for lifeline communication
2 / 5	Group 2 supports Basic Set, refer to your controller manual for instructions on setting up these features.

Supported Command Classes (17):

Association Group Information V3	Association V2
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	