

## Z-Wave Protocol Implementation Conformance Statement

### illumino WallMote 7

#### General Information

<b>Product Identifier:</b>	ZWA022-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.04
<b>Z-Wave Certification #:</b>	ZC12-21080284

#### Product Features

<b>Battery Quantity</b>	2
<b>Z-Wave Scene Type</b>	Central Scene
<b>Battery Type</b>	CR2032
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0016
<b>Z-Wave Product Type:</b>	0x0102
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.9
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Central Scene Device / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

illumino WallMote 7

## Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 5            This is the Lifeline group
- 2 / 5            Issued Basic Set/ Switch Binary Set when Top button press. (The command class is determined by Parameter 2)
- 3 / 5            Issued Multilevel Switch Set when Top button press.
- 4 / 5            Issued Basic Set/ Switch Binary Set when Bottom button press. (The command class is determined by Parameter 2)
- 5 / 5            Issued Multilevel Switch Set when Top button press.
- 6 / 5            Issued Basic Set/ Switch Binary Set when Bottom button press. (The command class is determined by Parameter 2)
- 7 / 5            Issued Multilevel Switch Set when Top button press.

**Supported Command Classes (17):**

- Association Group Information V3
- Battery
- Configuration V4
- Firmware Update Meta-Data V5
- Manufacturer Specific V2
- Powerlevel
- Supervision
- Version V3
- Z-Wave Plus Info V2
- Association V3
- Central Scene V3
- Device Reset Locally
- Indicator V3
- Multi-Channel Association V4
- Security S2
- Transport Service V2
- Wake Up V2