

## Z-Wave Protocol Implementation Conformance Statement

### illumino Dimmer Switch

#### General Information

<b>Product Identifier:</b>	ZWA037-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC12-21080285

#### Product Features

<b>Switch Load Capacity Watts</b>	500W
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Electric Load Type</b>	Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) Fluorescent Incandescent Inductive (e.g. Motor) LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Volt-Ampere</b>	120
<b>Switch Type</b>	Toggle
<b>Color</b>	White
<b>Switch Load Capacity Current</b>	4.1

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## illumino Dimmer Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0025
<b>Z-Wave Product Type:</b>	0x0103
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.9
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5	Lifeline group.
2 / 5	Issued when Top button press. (The command class is determined by Parameter 82)
3 / 5	Issued when Top button press or hold and release.
4 / 5	Issued when Bottom button press.(The command class is determined by Parameter 82)
5 / 5	Issued when Bottom button press or hold and release.
6 / 5	Issued when External Switch press.(The command class is determined by Parameter 82).
7 / 5	Issued when External Switch press or hold and release.
8 / 5	Issued when Top/ Bottom button press.(The command class is determined by Parameter 82).
9 / 5	Issued when Top/Bottom button press or hold and release.

**Supported Command Classes (19):**

Association Group Information V3	Association V3
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V4
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	