

## Z-Wave Protocol Implementation Conformance Statement

### illumino Wall Switch

#### General Information

<b>Product Identifier:</b>	ZWA038-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.02
<b>Z-Wave Certification #:</b>	ZC12-21080286

#### Product Features

<b>Color</b>	White
<b>Switch Load Capacity Watts</b>	1800
<b>Switch Load Capacity Current</b>	15
<b>Switch Type</b>	Toggle
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Neutral Wire Required</b>	Yes
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)

#### Z-Wave Product Information

<b>Supports Z-Wave Beaming Technology?</b>	Yes
--	-----

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## illumino Wall Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0026
<b>Z-Wave Product Type:</b>	0x0103
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.9
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5	Lifeline group.
2 / 5	Top button set ON/OFF
3 / 5	Bottom button set ON/OFF
4 / 5	External switch set ON/OFF
5 / 5	Top and Bottom button set ON/OFF

**Supported Command Classes (19):**

Association Group Information V3	Association V3
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V4
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Binary V2
Transport Service V2	Version V3
Z-Wave Plus Info V2	