

Z-Wave Protocol Implementation Conformance Statement

Mini Smart Plug

General Information

Product Identifier:	N4001
Brand Name:	
Product Version:	HW: 255 FW: 1.255
Z-Wave Certification #:	ZC10-21087048

Product Features

Color	White
Electric Load Type	Fluorescent Incandescent LED
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	1800W

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x4001
Z-Wave Product Type:	0xAC01
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Mini Smart Plug

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 3 Z-Wave Lifeline
- 2 / 5 When the output of the N4001 socket is changed, On (0xFF) or Off (0x00). The N4001 will automatically send out a related basic Set (0x0F) command. Off (0x00) to its associated group.

Supported Command Classes (17):

- Association Group Info
- Basic V2
- Device Reset Locally
- Manufacturer Specific V2
- Notification V8
- Security S0
- Supervision
- Transport Service V2
- Z-Wave Plus Info V2
- Association V2
- Configuration
- Firmware Update Meta-Data V4
- Multi-Channel Association V3
- Powerlevel
- Security S2
- Switch Binary
- Version V2

Controlled Command Classes (1):

- Basic V2