

Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Switch

General Information

Product Identifier:	61301/ZW4008
Brand Name:	iDevices
Product Version:	HW: 255 FW: 5.55
Z-Wave Certification #:	ZC10-21107058

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Current	15
Switch Load Capacity Watts	1800
Switch Type	Decorator Paddle Push with Indicator
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3136
Z-Wave Product Type:	0x4952
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Switch

Association Group Information

Group # / Max Description

Nodes

- 1 / 5 Lifeline. Supports device reset locally and receives unsolicited status updates
- 2 / 5 Association group 2 supports basic set and is controlled by single pressing the button
- 3 / 5 Association group 3 supports basic set and is controlled by double pressing the button

Supported Command Classes (18):

- | | |
|--------------------------|------------------------------|
| Application Status | Association Group Info |
| Association V2 | Basic V2 |
| Central Scene V3 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Powerlevel |
| Scene Activation | Scene Actuator Conf |
| Security S2 | Supervision |
| Switch Binary V2 | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

- Basic V2