

Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Dimmer

General Information

Product Identifier:	61303/ZW3010
Brand Name:	iDevices
Product Version:	HW: 255 FW: 5.55
Z-Wave Certification #:	ZC10-21107056

Product Features

Electric Load Type	Dimmable LED Incandescent
Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Watts	300
Switch Type	Decorator Paddle Push with Indicator
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3236
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Dimmer

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 5 Association Group 1 (Lifeline) supports Device Reset Locally and receives unsolicited status updates.
- 2 / 5 Association Group 2 supports Basic Set and is controlled by single pressing the button.
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the button

Supported Command Classes (16):

- Application Status
- Association V2
- Central Scene V3
- Device Reset Locally
- Manufacturer Specific V2
- Security S2
- Switch Multilevel V4
- Version V3
- Association Group Info
- Basic V2
- Configuration V4
- Firmware Update Meta-Data V4
- Powerlevel
- Supervision
- Transport Service V2
- Z-Wave Plus Info V2

Controlled Command Classes (1):

- Basic V2