

Z-Wave Protocol Implementation Conformance Statement

In-Wall Tamper Resistant Smart Outlet

General Information

Product Identifier:	61304/ZW1002
Brand Name:	iDevices
Product Version:	HW: 255 FW: 5.51
Z-Wave Certification #:	ZC10-21107057

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Current	15A
Switch Load Capacity Watts	1800W
Switch Type	Push Button Illuminated

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3235
Z-Wave Product Type:	0x4952
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Tamper Resistant Smart Outlet

Association Group Information

Group # / Max Description

Nodes

1 / 5 Z-Wave Plus Lifeline

2 / 5 Association Group 2 supports basic set and is controlled by single pressing the button

3 / 5 Association Group 3 supports basic set and is controlled by double pressing the button

Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2