

## Z-Wave Protocol Implementation Conformance Statement

### Multi Sensor

#### General Information

<b>Product Identifier:</b>	FGT-0002
<b>Brand Name:</b>	MITSUMI
<b>Product Version:</b>	HW: 1 FW: 7.14:01.00
<b>Z-Wave Certification #:</b>	ZC12-22010329

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0016
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.14.3
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

**Group # / Max**    **Description**

##### Nodes

1 / 5            Association Group 1 (Lifeline)

##### Supported Command Classes (19):

Association Group Information (AGI) V3	Association V2
Basic V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multilevel Sensor V11	Notification V8
Powerlevel	Security 2
Supervision	Transport Service V2

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

**Multi Sensor**