

## Z-Wave Protocol Implementation Conformance Statement

### 4 in 1 Multi-Sensor

#### General Information

<b>Product Identifier:</b>	PST10-US
<b>Brand Name:</b>	Philio
<b>Product Version:</b>	HW: 01 FW: 01.01:01.01
<b>Z-Wave Certification #:</b>	ZC14-21120029

#### Product Features

<b>Battery Type</b>	CR123A
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.15.1
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor DT / Reporting Sleeping Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 4 in 1 Multi-Sensor

2 / 5

### Supported Command Classes (19):

Association Group Information (AGI) V3

Battery

Device Reset Locally

Indicator V3

Multi Channel Association V3

Notification V8

Security 0

Supervision

Version V3

Z-Wave Plus Info V2

Association V2

Configuration V4

Firmware Update Meta Data V5

Manufacturer Specific V2

Multilevel Sensor V11

Powerlevel

Security 2

Transport Service V2

Wake Up V2