

Z-Wave Protocol Implementation Conformance Statement

HOPPE eHandle ConnectSense

General Information

Product Identifier:	E0400Z-EF
Brand Name:	HOPPE eHandle ConnectSense
Product Version:	HW: 1 FW: 8.20
Z-Wave Certification #:	ZC12-22050338

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Type	LS14500
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0002
Z-Wave Product Type:	0x0701
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.15.4
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

HOPPE eHandle ConnectSense

- 2 / 5 Transmits a Basic command to the devices in thisgroup when the window has been opened/closed
- 3 / 5 Transmits a Basic command to the devices in this group when the window has been tilted/closed
- 4 / 5 Transmits a Basic command to the devices in this group when the eHandle ConnectSense for windows has detected a burglary attempt

Supported Command Classes (19):

- Association Group Information (AGI) V3
- Battery
- Configuration V4
- Firmware Update Meta Data V5
- Manufacturer Specific V2
- Notification V8
- Security 0
- Supervision
- Version V3
- Z-Wave Plus Info V2
- Association V2
- Binary Sensor V2
- Device Reset Locally
- Indicator V3
- Multi Channel Association V3
- Powerlevel
- Security 2
- Transport Service V2
- Wake Up V2