

Z-Wave Protocol Implementation Conformance Statement

Dimmer-Control

General Information

Product Identifier:	FGD-212
Brand Name:	Nice
Product Version:	HW: 2 FW: 3.05:03.05
Z-Wave Certification #:	ZC10-22037071

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x0102
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 8	"On/Off (S1)" is used to turn the associated devices on/off.
3 / 8	"Dimmer (S1)" is used to set the associated devices to a certain level.
4 / 8	"On/Off (S2)" is used to turn the associated devices on/off.
5 / 8	"Dimmer (S2)" is used to set the associated devices to a certain level.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Dimmer-Control

Supported Command Classes (21):

Application Status	Association Group Info
Association V2	Basic
Configuration	CRC-16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Multi Channel Association V3	Multi Channel V4
Notification V5	Powerlevel
Protection V2	Security 0
Sensor Multilevel V4	Switch All
Switch Multilevel V3	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (3):

Basic	Scene Activation
Switch Multilevel V3	