

## Z-Wave Protocol Implementation Conformance Statement

### Motion-Control

#### General Information

<b>Product Identifier:</b>	FGMS-001
<b>Brand Name:</b>	Nice
<b>Product Version:</b>	HW: 1 FW: 3.04:03.04
<b>Z-Wave Certification #:</b>	ZC10-22037076

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1002
<b>Z-Wave Product Type:</b>	0x0801
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default)
2 / 5	"Motion" is assigned to the motion sensor - sends Basic Set command frames to the associated devices.
3 / 5	"Tamper" is assigned to the tamper - sends tamper alarm and alarm cancellation frames to the associated devices.
4 / 5	"Motion BC" is assigned to the motion sensor - sends motion detection and alarm cancellation frames to the associated devices. Provides backward compatibility with controllers not supporting Z-Wave+ protocol.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Motion-Control

5 / 5 "Tamper BC" is assigned to the tamper - sends tamper alarm and alarm cancellation frames to the associated devices. Provides backward compatibility with controllers not supporting Z-Wave+ protocol.

### Supported Command Classes (20):

Application Status	Association Group Info
Association V2	Basic
Battery	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific V2
Multi Channel Association V2	Notification V5
Powerlevel	Security 0
Sensor Alarm	Sensor Binary
Sensor Multilevel V8	Version V2
Wake Up V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic