

## Z-Wave Protocol Implementation Conformance Statement

### On/Off-Control

#### General Information

<b>Product Identifier:</b>	FGS-223
<b>Brand Name:</b>	Nice
<b>Product Version:</b>	HW: 3 FW: 3.04
<b>Z-Wave Certification #:</b>	ZC10-22047084

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1000
<b>Z-Wave Product Type:</b>	0x0203
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 5	"On/Off (S1)" is assigned to S1 input terminal (uses Basic command class).
3 / 5	"Dimmer (S1)" is assigned to S1 input terminal (uses Switch Multilevel command class).
4 / 5	"On/Off (S2)" is assigned to S2 input terminal (uses Basic command class).
5 / 5	"Dimmer (S2)" is assigned to S2 input terminal (uses Switch Multilevel command class).

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## On/Off-Control

### Supported Command Classes (20):

Application Status	Association Group Info
Association V2	Basic
Binary Switch	Central Scene V2
Configuration	CRC-16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Multi Channel Association V3	Multi Channel V4
Notification V5	Powerlevel
Protection V2	Security 0
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (3):

Basic	Notification V5
Switch Multilevel V3	