



## Z-Wave Protocol Implementation Conformance Statement

# Glass Break Sensor

### General Information

<b>Product Identifier:</b>	Glass Break Sensor
<b>Brand Name:</b>	Ring
<b>Product Version:</b>	HW: 01 FW: 01.05:01.01
<b>Z-Wave Certification #:</b>	ZC14-21120039

### Product Features

<b>Battery Quantity</b>	3
<b>Battery Type</b>	AA
<b>Color</b>	White
<b>Outdoor Use</b>	Yes

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	US_LR, U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0A01
<b>Z-Wave Product Type:</b>	
<b>Z-Wave Hardware Platform:</b>	ZGM130S037HGN2 / ZGM130S037HGN1
<b>Z-Wave Development Kit Version:</b>	7.16.3
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor DT / Listening Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Glass Break Sensor

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5

**Supported Command Classes (16):**

Association Group Information (AGI) V3	Association V2
Battery V3	Configuration V4
Device Reset Locally	Firmware Update Meta Data V5
Indicator V3	Manufacturer Specific V2
Multi Channel Association V3	Notification V8
Powerlevel	Security 2
Supervision	Transport Service V2
Version V3	Z-Wave Plus Info V2