

Z-Wave Protocol Implementation Conformance Statement

RGBW-Control

General Information

Product Identifier:	FGRGBW-442
Brand Name:	Nice
Product Version:	HW: 2 FW: 5.00:05.00:01.00
Z-Wave Certification #:	ZC10-22047077

Product Features

Color	White
--------------	-------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x0902
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch - Color Tunable Multilevel / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 5	"RGBW Sync" allows to synchronize state of other RGBW-Control devices.
3 / 5	"On/Off (S1)" is used to turn the associated devices on/off reflecting S1 operation.
4 / 5	"Dimmer (S1)" is used to change level of associated devices reflecting S1 operation.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

RGBW-Control

- 5 / 5 "On/Off (S2)" is used to turn the associated devices on/off reflecting S2 operation.
- 6 / 5 "Dimmer (S2)" is used to change level of associated devices reflecting S2 operation.
- 7 / 5 "On/Off (S3)" is used to turn the associated devices on/off reflecting S3 operation.
- 8 / 5 "Dimmer (S3)" is used to change level of associated devices reflecting S3 operation.
- 9 / 5 "On/Off (S4)" is used to turn the associated devices on/off reflecting S4 operation.
- 10 / 5 "Dimmer (S4)" is used to change level of associated devices reflecting S4 operation.

Supported Command Classes (23):

Application Status	Association Group Information V2
Association V2	Central Scene V3
Color Switch V3	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta Data V4	Manufacturer Specific V2
Meter V3	Multi Channel Association V3
Multi Channel V4	Multilevel Sensor V11
Notification V8	Powerlevel
Protection V2	Security 0
Security 2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Color Switch V3