

## Z-Wave Protocol Implementation Conformance Statement

### Plug-Control E/F

#### General Information

<b>Product Identifier:</b>	FGWPx-102
<b>Brand Name:</b>	Nice
<b>Product Version:</b>	HW: 2 FW: 3.02:03.02
<b>Z-Wave Certification #:</b>	ZC10-22047083

#### Product Features

<b>Color</b>	White
--------------	-------

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1003
<b>Z-Wave Product Type:</b>	0x0602
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 10	"On/Off (Button)" devices in this group will be switched on or off when relay status is changed using the B-button (uses Basic command class).
3 / 10	"On/Off (Power)" devices in this group will be switched on or off depending on the current load (uses Basic

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-Control E/F

### Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic
Binary Switch	Configuration
CRC-16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific V2
Meter V2	Multi Channel Association V3
Notification V5	Powerlevel
Security 0	Sensor Multilevel V5
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (2):

Basic	Multi Channel V4
-------	------------------