

## Z-Wave Protocol Implementation Conformance Statement

### Zooz 4-in-1 Sensor 700 Series

#### General Information

<b>Product Identifier:</b>	ZSE40AU-700
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 3 FW: 32.32
<b>Z-Wave Certification #:</b>	ZC12-22040335

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR123A
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand, Brazil, Malaysia, Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x2101
<b>Z-Wave Product Type:</b>	0x2021
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Zooz 4-in-1 Sensor 700 Series

2 / 5            The 4-in-1 sensor supports Group 2 with up to five devices for basic set reports.

### Supported Command Classes (20):

Application Status	Association Group Information (AGI) V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta Data V5	Indicator V3
Manufacturer Specific V2	Multi Channel Association V3
Multilevel Sensor V11	Notification V8
Powerlevel	Security 0
Security 2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2